ST-JL05-20S-C2-10000

Product Details



Features

Crimp termination type, Socket stamped contact, Contact size : #20, Silver plating, Applicable Wire Size : #26 to #22 AWG, Reel (10,000 pieces/reel)

Part Number	ST-JL05-20S-C2-10000
Status	Active
Number of Positions	_
Rated Current (per contact), when embedded in the insulator	5 A max. [Applicable Wire (Cross-sectional Area of Conductor) : 0.3 mm ²] 3 A max. [Applicable Wire (Cross-sectional Area of Conductor) : 0.2 mm ²] 2 A max. [Applicable Wire (Cross-sectional Area of Conductor) : 0.13 mm ²]
Waterproof/ Non-waterproof	
Connector Type	Contacts
Shell Size	-
Contact Arrangement Code	-
Contact Type	Socket
insert rotation position (degrees)	-
Contact Size	#20
Contact Size X No. of Contacts	-
Wire Termination Method	Crimp
Applicable Wire Size (AWG/Cross-sectional Area of	#26 to #22AWG / 0.13 mm 2 to 0.3 mm 2 / $\Phi 1.2$ mm to $\Phi 1.7$ mm

Conductor/Insulation outer	
diameter)	
Hand Crimping Tool	Please contact JAE for detail
Semi-automatic Crimp tool	Please contact JAE for detail
Outer Shell Color	-
Material of Contact	Copper alloy
Finish of Contact in Connecting Area	Silver plating
Contact Resistance	15 milliohm max. (#24, #22 AWG)
	27 milliohm max. (#26 AWG)
Dielectric Withstanding	
Voltage (1 minute)	
Insulation Resistance	-
Operating Temperature Range	-55 Deg. C to +125 Deg. C
Applicable Contacts	
Applicable Accessory	-
Applicable Product Part	
Numbers	
RoHS compliant	10 substances (2011/65/EU, (EU)2015/863)
REACH compliant	
Remarks	Stamped contact, Reel (10,000 pieces)

Notice

- The values specified in this web site are only for reference. The products and their specifications are subject to change without notice. Contact our sales staff for further information before considering or ordering any of our products.
 For purchase, a product specification must be agreed upon.
- 2. Users are requested to provide protection circuits and redundancy circuits to ensure safety of the equipment, and sufficiently review the suitability of JAE's products to the equipment.
- The products presented in this web site are designed for the uses recommended below.
 We strongly suggest you contact our sales staff when considering use of any of the products in

any other way than the recommended applications or for a specific use that requires an extremely high reliability.

- (1) Applications that require consultation:
 - * Please contact us if you are considering use involving a quality assurance program that
 - you specify or that is peculiar to the industry, such as:
 - Automotive electrical components, train control, telecommunications devices (mainline), traffic light control, electric power, combustion control, fire prevention or security systems, disaster evention equipment, etc.
 - * We may separately give you our support with a quality assurance program that
 - you specify, when you think of a use such as :
 - Aviation or space equipment, submarine repeaters, nuclear power control systems, medical equipment for life support, etc.
- (2) Recommended applications include:
 - * Computers, office appliances, telecommunications devices (terminals, mobile units), measuring equipment, audiovisual equipment, home electric appliances, factory automation equipment, etc